

HT99A Spy Button Camera Instruction

Specification:

- Size&weight: 66mm*21mm*20mm, 35g
- Video Resolution: 1280X720 30fps H.264 MOV
- **Photo resolution** (Just taking photos in the WIFI mode): 1280*960 JPEG
- Supports looping recording, create and save a file every 3min
- Built-in rechargeable high temperature resistance polymer lithium battery 500mAH. Record approx. 100mins when getting fully charged.
- Connect to USB 5V external power supply to record when charging. In the recording while charging
- The date and time stamp on video will be auto synchronized with your mobile phones after connecting wifi.
- The Video/Photo function can be chosen after connecting wifi with your mobile phone.

Operation Instruction:

1. ON/OFF button

- 1) Turn On: Short press the on/off button for 1s, the green light will flash 3 times then be off, which states that it enters the recording mode.
- 2) Turn Off: Long press the ON/OFF button for 3s, the green light will be off that shows that it turns off. In the recording mode, long press the ON/OFF button for 3s, the green light will flash 1 time that indicates it saves video files and turns off.

2. REC/STOP/WIFI button:

- 1) Stop recording: In the recording mode, short press the REC/STOP/WIFI button for 1s, the green light will stay on that shows that it enters the stop recording mode;
- 2) Recording mode: Short press the REC/STOP/WIFI button for 1s, the green light will slowly flash for 3 times then be off, and then enter the recording mode;
- 3) Long press the REC/STOP/WIFI button for 3s in the stop recording mode, the blue light will be on that indicates the WIFI is on;
- 4) Long press the REC/STOP/WIFI button for 3s in the WIFI mode, the blue light will be off and then the WIFI is off.

3. Wifi Mode

- 1) Download the APP:
 - a) IOS system: search ismart dv in APP store
 - b) Android system: search ismart dv in Google Play
- 2) WIFI name: MSL_Retailxxx
- 3) WIFI code: 1234567890

Other auxiliary functions:

1. Automatically power off: when inside Lithium-ion battery power is lower than 3.6V, the green light continuously flickers for 5 seconds then saves files automatically and powers off.
2. Charging: with built-in long life rechargeable high temperature resistant polymer lithium battery. Please charge it about 3 hours before using. When it is charging, please turn it off.
3. Connect to PC to charge: connect it to PC with USB cable, the red light lasting means it is in charging mode; the red light goes off means it gets fully charged.
4. Charging with 5V 1A charger: Connect it to 5V charger with USB cable, the red light lasting means it is in charging mode; the red light goes off means it gets fully charged.
5. Connect to PC: After connecting to PC with USB cable, turn on the camera and blue light stays on and then will recognize the TF card.
6. Note: Please turn camera off before connecting to PC.
7. We suggest to use high quality Class 10 TF card, to avoid the problem of camera don't recognize to PC ex.
8. If the Switch button is not working, please try to press the reset button.