


HT98A Wifi Pen Camera



Specification:

- Size&weight: 15*150mm,50g
- **Video Resolution:** 1280X720 30fps H.264 MOV(If you need,you can ask the seller to update: 1920*1080 30fps H.264 MOV)
- **Photo resolution:**(Just taking photos in the WIFI mode): 1280*960 JPEG
- Supports looping recording,create and save a

file every 3min.

- Built-in high speed Class 10 TF card,you can choose 8GB/16GB/32GB or 64GB.But don't support the external replacement.
- Built-in rechargeable high temperature resistant polymer lithium battery.Built-in Charger manage IC. 300mAH. Record approx. 30mins when getting fully charged. (Battery can be changeable with the battery provided by manufacturer)
- **Charge voltage:**DC 5V
- **Material:**Metal,UV Baking varnish
- Connect to USB 5V external power supply to record when charging.In the recording while charging state,its temperature will be higher than 50°C.After testing, it can continuously work for 96h,and it is safe, but please don't use this function for a long time.
- **Product working temperature:** Because of its particularity and limited internal volume, when it works for about 10mins,the temperature of its metal shell will be around 40°C-45°C, but

please do not worry about it.

Operation Instruction:

1. Power on: Press the Switch button for 1s,the blue light slowly blinks for 3 times then goes off shows that the WIFI is on and the camera is in the recording mode.

2. Power off: In the standby mode, long press the Record/Stop button for 3s,the blue light goes off, it means the camera is off.

In the recording mode, long press the Record/Stop button for 3s, the blue light flickers for 1 time, then saves file and powers off.

3. Recording:

1)**Power on recording:** Short press Switch button for 1s, blue light flashes 3 times then goes off, that means it enters the recording mode.

2)**Standby mode:** In the recording mode, press the Switch button then you can stop recording and save the files.At the same time,the blue light is on which shows it enters the standby

mode.

4. Wifi Mode

- 1)Wifi is starting when powers on.
- 2)Download App:
 - A. IOS systems: search **ismart dv** in App store
 - B. Android systems: search **ismart dv** in google play
- 3)Wifi name: **HT98A_XXXXXX**
- 4)Wifi default code: **1234567890**
- 5)The date and time stamp on video will be auto synchronized with your mobile phone's after connecting wifi.
- 6)The Video/Photo function can be chosen after connecting wifi with your mobile phone.

5. Other auxiliary functions:

- 1)Automatically power off: when inside Lithium-ion battery power is lower than 3.6V, the blue light continuously flickers for 5 seconds then saves files automatically and powers off.
- 2)Charging: with built-in long life rechargeable high temperature resistant polymer lithium battery.Please charge it about 3 hours before

using. When it is charging, please turn it off.

- 3)Connect to PC to charge: connect it to PC with USB cable,the red light lasting means it is in charging mode; the red light goes off means it gets fully charged.
- 4)Charging with 5V 1A charger: Connect it to 5V charger with USB cable,the red light lasting means it is in charging mode; the red light goes off means it gets fully charged.
- 5)Connect to PC: After connecting to PC with USB cable, turn on the camera and blue light stays on and then will recognize the TF card. Note: Please turn camera off before connecting to PC.

6)If the Switch button is not working, please try to press the Reset button.

6. Tips:

Product working temperature: Because of its particularity and limited internal volume, when it works for about 20mins,the temperature of its metal shell will be around 40°C, but please do not worry about it.

7. Package:

- 1 x Wifi Camera
- 1 x Micro USB Cable
- 1 x FPV Cable
- 1 x User Manual

